

# MRM-70D UHF Dual-Channel Receiver Module

## Features

- Preset 16 auto-scannable frequencies.
- “SCAN” and “ACT” buttons, interference warning indicator and “Sensitivity” adjustor.
- An easy-to-read LED channel display, 5-segment RF and AF meters.
- Diversity receiving technology for optimum reception quality.
- Modular design allows for easy installation and replacement.



## Specifications

Frequency Band	UHF 480 – 934 MHz
Bandwidth	24 MHz
Preset Channels	16
Channel Setting	Manually set up the desired channel or scan for an open channel. Press the ACT button to synchronize the transmitter and receiver
Display	Channel, RF/AF meters, sensitivity meters and interference warning indicator
Receiving Mode	MCU-controlled diversity receiving
Sensitivity	S/N > 80 dB at 10 dB $\mu$ V
S/N Ratio	> 100 dBA
THD	< 0.5% @ 1 kHz
Frequency Response	50 Hz – 18 kHz
AF Output	610 mV RMS
Power Supply	DC 12 – 15 V
Dimensions	220 × 57 × 183 mm (W × H × D)
Weight	Approx. 597 g