

E-5S Single-sided Earphone

Features

- For MTG-100R / MTG-100Ra digital receivers.



Specifications

Driver Unit	24 mm
Frequency Response	100 Hz – 20 kHz
Sensitivity	108 dB \pm 3 dB @ 1 mW
Max. Input Power	100 mW
Impedance	32 \pm 15% Ω @ 1 kHz 1 mW
Cable Length	120 cm
Connector	3.5 mm TRS
Weight	Approx. 14 g